

PRO+ Series

PRO+ Series circuit breaker design chart

PRO+ Series sulakemitoitustaulukko

				Number of luminaires per circuit breaker Kytettävien valaisimien enimmäismäärä			
				B10 A	B16 A	C10 A	C16 A
PRO+ 100	200mA	15 W	0,08 A	7	12	10	18
	330mA	23 W	0,11 A				
	440mA	30 W	0,14 A				
	600mA	41 W	0,19 A				
PRO+ 200	380mA	50 W	0,24 A	7	12	10	18
	460mA	60 W	0,28 A				
	530mA	68 W	0,32 A				
PRO+ 400	380mA	75 W	0,35 A	4	8	6	12
	460mA	90 W	0,41 A				
PRO+ 500	380mA	99 W	0,45 A	4	8	6	12
	460mA	120 W	0,54 A				

	Inrush current peak Käynnistysvirtapiikki	Earth leakage current Maavuotovirta
PRO+ 100	53A, t = 200µs (50 % of Ipeak)	0,13 mA
PRO+ 200	57A, t = 210µs (50 % of Ipeak)	0,18 mA
PRO+ 400	62A, t = 330µs (50 % of Ipeak)	0,15 mA
PRO+ 500	62A, t = 330µs (50 % of Ipeak)	0,15 mA