

PRO Flow S - Z models

PRO Flow S - Z models circuit breaker design chart
PRO Flow S - Z mallit sulakemitoitustaulukko

Number of luminaires per circuit breaker
Kytettävien valaisimien
enimmäismäärä

				Type	B10 A	B16 A	C10 A	C16 A
PRO Flow S 12-	350	14 W	0,1 A	Type 1a	12	20	20	32
	420	17 W	0,1 A					
	500	20 W	0,1 A					
	600	23 W	0,1 A					
	700	27 W	0,1 A					
	850	33 W	0,2 A					
	1000	39 W	0,2 A					
PRO Flow S 14-	350	16 W	0,1 A	Type 1a	12	20	20	32
	420	19 W	0,1 A					
	500	22 W	0,1 A					
	600	26 W	0,1 A					
	700	31 W	0,1 A					
	850	37 W	0,2 A					
	1000	44 W	0,2 A					
PRO Flow S 24-	350	26 W	0,1 A	Type 1b	3	6	6	10
	420	31 W	0,2 A					
	500	37 W	0,2 A					
	600	44 W	0,2 A					
	700	52 W	0,2 A					
	850	63 W	0,3 A					
	1000	74 W	0,3 A					
PRO Flow S 30-	350	32 W	0,2 A	Type 1b	3	6	6	10
	420	38 W	0,2 A					
	500	45 W	0,2 A					
	600	54 W	0,3 A					
	700	63 W	0,3 A					
	850	76 W	0,3 A					
	1000	90 W	0,4 A					

Type	Inrush current peak Käynnistysvirtapiikki	Earth leakage current Maavuotovirta
Type 1a	21A, t = 300 μ s (50 % of I _{peak})	0,2 mA
Type 1b	65A, t = 330 μ s (50 % of I _{peak})	0,2 mA