

PRO+ Series circuit breaker design chart

PRO+ Series sulakemitoitustaulukko

				Number of luminaires per circuit breaker			
				Kytettävien valaisimien enimmäismäärä			
				B10 A	B16 A	C10 A	C16 A
PRO+ 100	200mA	14 W	0,08 A	6	10	10	16
	330mA	22 W	0,11 A				
	440mA	29 W	0,14 A				
	600mA	40 W	0,19 A				
PRO+ 200	380mA	50 W	0,24 A	6	10	10	17
	460mA	60 W	0,28 A				
	530mA	68 W	0,32 A				
PRO+ 400	380mA	75 W	0,35 A	3	5	5	8
	460mA	90 W	0,41 A				
PRO+ 500	310mA	81 W	0,37 A	3	5	4	7
	380mA	99 W	0,45 A				
	460mA	120 W	0,54 A				

	Inrush current peak Käynnistysvirtapiikki	Earth leakage current Maavuotovirta
PRO+ 100	32A, t = 355µs (50 % of I _{peak})	0,17 mA
PRO+ 200	42A, t = 238µs (50 % of I _{peak})	0,15 mA
PRO+ 400	65A, t = 268µs (50 % of I _{peak})	0,17 mA
PRO+ 500	80A, t = 250µs (50 % of I _{peak})	0,09 mA