

PRO+ Series Xi

PRO+ Series X circuit breaker design chart

PRO+ Series X sulakemitoitustaulukko

				Number of luminaires per circuit breaker			
				Kytettävien valaisimien enimmäismäärä			
				B10 A	B16 A	C10 A	C16 A
PRO+ 4Xi	100	99 W	0,5 A				
	120	120 W	0,6 A	4	7	7	12
	140	146 W	0,7 A				
PRO+ 6Xi	130	128 W	0,6 A				
	150	149 W	0,7 A	4	7	7	12
	180	180 W	0,8 A				
	220	218 W	1,0 A				
PRO+ 8Xi	150	154 W	0,7 A				
	200	198 W	0,9 A	4	7	7	12
	240	240 W	1,1 A				
	280	286 W	1,3 A				
PRO+ 12Xi	300	298 W	1,4 A				
	360	360 W	1,6 A	2	3	3	6
	430	436 W	2,0 A				

	Inrush current peak Käynnistysvirtapiikki	Earth leakage current Maavuotovirta
PRO+ 4Xi	13A, t = 1320µs (50 % of Ipeak)	0,22 mA
PRO+ 6Xi	13A, t = 1320µs (50 % of Ipeak)	0,22 mA
PRO+ 8Xi	13A, t = 1320µs (50 % of Ipeak)	0,22 mA
PRO+ 12Xi	2 x [13A, t = 1320µs] (50 % of Ipeak)	0,44 mA