

PRO+ Series

PRO+ Series circuit breaker design chart

PRO+ Series sulakemitoitustaulukko

				Number of luminaires per circuit breaker					
				Kytettävien valaisimien enimmäismäärä					
				TYPE B			TYPE C		
				10 A	16 A	20 A	10 A	16 A	20 A
PRO+ 100	8-200mA	5,5 W	0,04 A						
	8-300mA	8 W	0,04 A	19	30	37	31	50	61
	8-450mA	11 W	0,06 A						
	22-200mA	14 W	0,08 A						
	22-330mA	22 W	0,11 A	6	10	13	10	16	21
	22-440mA	29 W	0,14 A						
	22-600mA	40 W	0,19 A						
PRO+ 200	380mA	50 W	0,24 A						
	460mA	60 W	0,28 A	6	10	13	10	17	22
	530mA	68 W	0,32 A						
PRO+ 400	380mA	75 W	0,35 A	3	5	6	5	8	10
	460mA	90 W	0,41 A						
PRO+ 500	310mA	81 W	0,37 A						
	380mA	99 W	0,45 A	3	5	7	4	7	9
	460mA	120 W	0,54 A						

	Inrush current peak Käynnistysvirtapiikki	Earth leakage current Maavuotovirta
PRO+ 100 8LED	15A, t = 226µs (50 % of Ipeak)	0,15 mA
PRO+ 100 22LED	32A, t = 355µs (50 % of Ipeak)	0,17 mA
PRO+ 200	42A, t = 238µs (50 % of Ipeak)	0,15 mA
PRO+ 400	65A, t = 268µs (50 % of Ipeak)	0,17 mA
PRO+ 500	80A, t = 250µs (50 % of Ipeak)	0,09 mA